Conventional Sounder cum Strobe 24V

(Family-Fire)



Product Description

The fire alarm sounder strobe is a device design such that to produce sound and flashing when manual call point or detector sense any kind of fire activity. It has dual tone sound, and it is enough to make alert everyone inside the buildings, factories, malls, schools and colleges.



Application

- Shopping malls
- Residential buildings
- Industrial factories

Product features:

- Easy to install.
- Operates on 24 VDC.
- 100 db.
- Low current.



Conventional Sounder cum Strobe 24V

(Family- Fire)



Technical Specifications

General specifications	
Current consumption	100 mA / 150 mA
Operating voltage	DC 12 V / 24 V
Operating temperature	-10° C to 50° C
Humidity	- 95%</td
Colour	Red
Sounder level	100 dB
Electrical specifications	
Flashing intensity	>/- 1.2 ws.
Flashing period	= 1.5 s.</td
Mechanical specifications	
Weight	200gms
Dimensions	126 x 126 x 55 mm (W x h x D)
Housing	ABS plastic
Warranty	One year

Abbreviations	
S03	S- Sounder,
	03- Series

Datasheet Version with Date (29/07/2020)

