

# V Cop Gold GSM Hybrid



Vignaharta™

## Intrusion Alarm Panel

(Family - Intrusion)

### Product Description:

V-Cop Gold intrusion alarm panel is designed for banks, home, office security system. System can read inputs from 9 wired (microcontroller based) and 32 wireless sensors to detect an emergency condition. An LCD display situated on the front panel, which gives the visual indication of various activities carried out. It can display exact cause of alarm. It has rare ability to connect 2-wire conventional smoke or heat detectors. Any alarm or trouble conditions are reported in both audio-visual manners.



### Application:

- Home security
- Shops
- Banks
- Jewelry shops

### Product Features:

- 16 x 2 backlight LCD display
- Tactile 18 keys keypad (external keypad of 18 key supported\*)
- Inbuilt GSM auto dialer (compatible to PSTN dialer also \*)
- 10 voice and 10 SMS reporting number support
- 20 second pre-recorded voice message. Message playback facility
- Up to 100 number of event support
- Provision for partial arm and auto arm / disarm (day/night mode) zone facility
- Scheduled base arming & disarming
- Arming and disarming through keypad, wireless key fob, SMS and using android app.
- Upgraded to IP connectivity ready (optional\*)

### Technical Specifications:



Vignaharta Technologies Pvt. Ltd.  
(formally known as Realty Automation and Security Systems Pvt. Ltd)  
[www.vignaharta.in](http://www.vignaharta.in)

Vignaharta™

Automation | Safety | Security | Surveillance

# V Cop Gold GSM Hybrid



Vighnaharta™

## Intrusion Alarm Panel

(Family - Intrusion)

<b>General specifications</b>	
Operating temperature	0° C to 50° C
Humidity	0 to 95 % Rh
Colour	Off White
Sound level	85 dB internal buzzer
Enclosures	Metal body
<b>Electrical specifications</b>	
Power supply	230 V AC
Voltage and current rating	15 V, 2 A
Battery back up	Up to 8 Hrs - 12 Hrs (support 1.2 Ah to 7 Ah battery)
Standby power	180 mA
Power consumption	1.2 A on load
Number of zones	9 Wired & 32 wireless zones
Zone expander support	Yes, 10 zone expanders
Smoke zone	Yes, 1 dedicated zone out of 9 zone
Number of smokes connect	10-12 nos.
<b>Mechanical specifications</b>	
Weight	4.5 Kg
Dimensions	(L x W x H) 320 x 75 x 220 mm
Display	On board
Cable entry	Gland type
<b>LED indications and output</b>	
LED Colour	<ul style="list-style-type: none"><li>• Zone trouble</li><li>• System ARM</li><li>• System disarm / normal</li><li>• Power ON</li></ul>
Output	<ul style="list-style-type: none"><li>• Inbuilt GSM auto dialer</li><li>• Siren Output—1 to 20 min.</li><li>• 10 Voice &amp; SMS reporting</li><li>• 16*2 LCD display</li><li>• PFC relay output</li><li>• Audio buzzer</li><li>• Logs 99 events/alarms view support</li></ul>
<b>Certifications</b>	
	EDTC /STQC
<b>Warranty</b>	
	Standard 1 year



Vighnaharta™

Vighnaharta Technologies Pvt. Ltd.  
(formally known as Realty Automation and Security Systems Pvt. Ltd)  
[www.vighnaharta.in](http://www.vighnaharta.in)

Automation | Safety | Security | Surveillance

# V Cop Gold GSM Hybrid



Vignaharta™

## Intrusion Alarm Panel

(Family - Intrusion)

### Models and variants

	V cop Gold - PSTN, IP, Standalone
	V cop Silver – GSM, IP, Standalone

### Abbreviations

V- Cop Gold GSM Hybrid	V- Vignaharta Gold GSM, Hybrid – 9 wired and 32 wireless zone
------------------------	---

Datasheet version with date (V.2 Oct. 2020)



Vignaharta™

Vignaharta Technologies Pvt. Ltd.  
(formally known as Realty Automation and Security Systems Pvt. Ltd)  
[www.vignaharta.in](http://www.vignaharta.in)

Automation | Safety | Security | Surveillance